

IR(Infrared) CAT5 Extender

ITEM NO.: IE01




This extender kit allows you to add IR remote control for up to four A/V devices over a single Cat5e/6 cable. Devices can be controlled from up to 1200 meters away. The external power only requested at one side, either at sender or receiver side. 2 sets of IR emitter/receiver cable and one power adapter are included. Suitable for home theatre, lecture theatres, AV rooms, conference rooms, shop window and merchandising displays.

IE01 IR CAT5 Extender

- Extend IR (infrared) control signal up to 1.2KM over one CAT5/5e/6 cable.
- IR receiver frequency range: 30Khz to 60Khz.
- Supports up to 4 outputs.
- Support Bi-directional application.
- External power adapter requested either at transmitter or receiver unit.
- Package include IR CAT5 Extender Kit, 1 x power adapter, 2 x IR emitter cable, 2 x IR receiver cable.
- Option model: IR-CT01 IR emitter cable

Installation View:



Cable:

Link Cable recommend use high quality Cat.5e. UTP, STP or FTP cable.

Transmission Range:

Working distance up to 1.2KM.

RJ45 pin Define:

Video Link

- 1. Orange-white 12V
- 2. Orange 12V
- 3. Green-white GND
- 4. Blue RS485 A1
- 5. Blue-white RS485 B1
- 6. Green GND
- 7. Brown-white RS485 A2
- 8. Brown RS485 B2


LED Indication:

- GREEN Power on/off
- BLUE IR signal receiving
- RED IR signal emitting

Caution:

Do not put IR emitter cable near the IR Receiver cable that may cause IR not working.

Panel View:



Specification:

| ITEM NO. | IR Emitter | IR Receiver |
|-----------------------|----------------------|-------------|
| IR | 4 Port | 1 Port |
| IR Carrier Frequency | 30KHz ~ 60KHz | |
| Extender Distance | 1.2KM | |
| IR Operating Distance | 8 M | 10 M |
| IR Operating Angle | ± 30 deg | ± 55 deg |
| Power Supply | Regulated 12V / 0.5A | |
| Power Consumption | 100mA (Max) | |
| Dimensions | 88*95*30 (mm) | |
| Shipping Weight | 170 g | |

RoHS CE FC